

## Model No: RT300RF

## Digital Room Thermostat with RF

Radio frequency digital room thermostat with large backlit LCD display.

### Features

- Volt free contacts
- Stylish casing
- Desk stand
- Frequency 868 MHz (30 metre range)

Can be used for volt free and 230V applications.

Thermostat Supply:	2xAA Batteries
Receiver (Rx) Supply:	230Vac 50Hz
Rx Rating Max:	16 (5) A SPST
Rx Input/Output:	0 - 230V
Thermostat Scale:	5 - 35°C
Unit Size:	W-95 H-95 D-40
Boiler Control Size:	W-130 H-95 D-65

### RF Receiver Wiring

L	Live connection
N	Neutral connection
COM	Input
NO	Switched output

